XDM1000 Series Digital Multimeter Technical Specifications

| Function | Range ^[1] | Resolution | Accuracy: ± (% of reading + LSB) [2] |
|---------------------------------------|-----------------------------------|-------------------------|--------------------------------------|
| DC Voltage | 50.000 mV | 0.001 mV | 0.1% + 10 |
| | 500.00 mV | 0.01 mV | 0.05% + 5 |
| | 5.0000 V | 0.0001 V | 0.05% + 5 |
| | 50.000 V | 0.001 V | 0.05% + 5 |
| | 500.00 V | 0.01 V | 0.1% + 5 |
| | 1000.0 V ^[3] | 0.1 V | 0.1% + 10 |
| True RMS AC Voltage ^[4] | 500 mV – 750 V | 20 Hz – 45 Hz | 1% + 30 |
| | | 45 Hz – 65 Hz | 0.5% + 30 |
| | | 65 Hz – 1 kHz | 0.7% + 30 |
| | 500 uA | 0.01 uA | 0.15% + 20 |
| | 5000 uA | 0.1 uA | 0.15% + 10 |
| DC Command | 50 mA | 0.001 mA | 0.15% + 20 |
| DC Current | 500 mA | 0.01 mA | 0.15% + 10 |
| | 5 A | 0.0001 A | 0.5% + 10 |
| | 10 A ^[5] | 0.001 A | 0.5% + 10 |
| True RMS | 500 uA – 500 mA | 20 Hz – 1 kHz | 0.5% + 20 |
| AC Current ^[6] | 5 A – 10 A | | 1.5% + 20 |
| Resistance ^[7] | 500 Ω | 0.01 Ω | 0.15% + 10 |
| | 5 kΩ | 0.0001 kΩ | 0.15% + 5 |
| | 50 kΩ | 0.001 kΩ | 0.15% + 5 |
| | 500 kΩ | 0.01 kΩ | 0.15% + 5 |
| | 5 ΜΩ | $0.0001~\text{M}\Omega$ | 0.3% + 5 |
| | 50 MΩ | 0.001 ΜΩ | 1% + 10 |
| Diode | 3.0000 V | 0.0001 V | 1% + 10 |
| Continuity | 1000 Ω | 0.1 Ω | Adjustable threshold |
| Frequency | 10.000 Hz – 60 MHz ^[8] | / | ± (0.2% + 10) |
| Capacitance ^[9] | 50 nF – 500 uF | / | 2.5% + 10 |
| | 5 mF – 50 mF | 0.1 Ω | 5% + 10 |
| Temperature | K type, PT100 | | |
| Display | 55,000 | | |
| Record Interval | 15 mS – 9999.999 S | | |
| Record Length | 1,000 points | | |

^{[1] 10%} over range on all ranges, except 1,000 V DCV, 750 ACV, 10 A DCI, 10 A ACI, 50 M Ω resistance, and 50 mF capacitance.

- [2] 10% over range on all ranges, except 1,000 V DCV, 750 ACV, 10 A DCI, 10 A ACI, 50 M Ω resistance, and 50 mF capacitance. Specifications are for 30-minute warm-up, "Low" measurement rate and calibration temperature 18 $^{\circ}$ 28 $^{\circ}$ C.
- [3] For each additional volt over ± 500 VDC add 0.02 mV of error.
- [4] Specifications are for amplitude of sine wave input > 5% of range. 0.1% errors will be added when the range of input sine wave is 1% to 5%.
- [5] 30 seconds OFF after 30 seconds ON is recommend for the continuous current that higher than DC 7 A or AC RMS 7 A.
- [6] Specifications are for amplitude of sine wave input > 0.5% of range. For inputs from 1% to 5% of range, add 0.1% of range extra error.
- [7] Specifications are for 2-wire ohms using the relative operation of math. Without relative operation, add $\pm 0.20~\Omega$ additional error in 2-wire ohms function.
- [8] Except for special marks, when frequency ≤ 10M Hz, the specification is applicable to >1V AC input voltage, when frequency > 10 MHz, the specification is applicable to >3V AC input voltage.
- [9] Specifications are for using the relative operation of math. Using of non-film capacitor may generate additional errors. Specifications are for from 5% to 110% on ranges.

General Specifications

| Display Screen | 3.5-inch TFT LCD with resolution 480*320 | |
|------------------------|--|--|
| Operating | Full temperature from $0^{\circ}\mathbb{C}$ to $50^{\circ}\mathbb{C}$, 80% RH and $40^{\circ}\mathbb{C}$, non-condensing | |
| Environment | Storage Temperature: -20 $^{\circ}\mathrm{C}$ to 70 $^{\circ}\mathrm{C}$ | |
| Remote Interface | RS232 or USB Device | |
| Programmer Language | Standard SCPI, compatible with commands of main stream multimeters | |
| Warm Up Time | 30 minutes | |
| Dimension (W×H×D) | 200 x 86.5 x 64 (mm) | |
| Weight | 0.45 kg | |

V1.1.1

