

TKPH6A

FUNCTION	RANGE	RESOLUTION	ACCURAY
DC V	600mV	100 μ V	$\pm 1\%+2$ digit
	6V ~ 600V	1mV	$\pm 1\%+5$ digit
AC V	600mV	100 μ V	$\pm 1.2\%+5$ digit
	6V ~ 600V	1mV	$\pm 1.2\%+5$ digit
DC A	600 μ A~	0.1 μ A	$\pm 1.2\%+2$ digit
	6mA	1 μ A	
	60mA	10 μ A	$\pm 1.2\%+5$ digit
	600mA	100 μ A	
AC A	600 μ A	0.1 μ A	$\pm 1.5\%+2$ digit
	6mA	1 μ A	
	60mA	10 μ A	$\pm 1.5\%+5$ digit
	600mA	100 μ A	
Freg	6MHz~	1Hz	$\pm 1\%+3$ digit
	60MHz	10KHz	
Resistance	600ohm	0.1ohm	$\pm 1.2\%+5$ digit
	6Kohm~600Kohm	1ohm	$\pm 1.2\%+5$ digit
	6Mohm	1Kohm	$\pm 2\%+5$ digit
	60Mohm	10Kohm	$\pm 3\%+5$ digit
CAP	6 nF	1 pF	$\pm 3\%+5$ digit
	600 μ F	1 μ F	
Inductance	6mH~600mH	100 μ H	$\pm 3\%+10$ digit
Continuity	Buzzer sound at < approx 50ohm		
Diode	Test current at 1.5 mA		